


Kondensatoren			
Lfd.Nr.	Kapazität	Arb.-Spd.	Spitz.-Spd.
C 1	300cm	350V.~	2000V.Pfph.
C 2	75 cm±5%		
C 3	75 cm±5%		
C 4	5000cm ni	100V.=	
C 5	2µf Elektrolyt	180V.=	200V.=
C 6	100 cm		
C 7	5000cm ni	100V.=	
C 8	550PF ni	100V.=	
C 9	55 pf		
C 10	320 pf ±5%		
C 11	635 pf ±5%		
C 12	500cm±5%ni		
C 13	8µf Elektrolyt	350V.=	450V.=
C 14	8µf "	350V.=	450V.=
C 15	500cm ±2%		
C 16	2µf Elektrolyt	250V.=	350V.=
C 17	110 pf		
C 18	110 pf		
C 19	1µf Elektrolyt	250V.=	350V.=
C 20	25000 pf	250V.=	350V.=
C 21	5000cm ni	100V.=	
C 22	5000cm ni	100V.=	
C 23	2µf Elektrolyt	150V.=	200V.=
C 24	1µf	250V.=	350V.=
C 25	110 pf		
C 26	110 pf		
C 27	10PF ±10%		
C 28	55 pf		
C 29	5000 cm	100V.=	
C 30	300 cm	350V.=	
C 31	10µf Elektrolyt	25V.=	
C 32	1µf	150V.=	200V.=
C 33	10000cm	150V.=	
C 34	3µf	250V.=	350V.=
C 35	10000cm	450V.=	
C 36	20µf Elektrolyt	26V.=	
C 37	2µf	250V.=	350V.=
C 38	30000cm	300V.=450V.=	
C 39	660PF		
C 40	1000cm	350V.=	
C 41	10000cm	450V.=	550V.=
C 42	10000cm	450V.=	550V.=
C 43	5000cm	350V.=	2000V.-Prfph.
C 44	5000cm	350V.=	2000V.-Prfph.
C 45	1000PF		

Widerstände			
Lfd.Nr.	Widerstandwert	Belastung	
R 1	600 Ω	0.5	Watt
R 2	600 Ω	0.5	"
R 3	100000 Ω	0.5	"
R 4	500 Ω	1	" Draht
R 5	280 Ω	1	"
R 6	50000 Ω	1	"
R 7	20000 Ω	0.5	"
R 8	500000 Ω	0.5	"
R 9	50000 Ω	0.5	"
R 10	10000 Ω	1	" Draht
R 11	20000 Ω	1	"
R 12	1000 Ω	1	"
R 13	1 M Ω	0.5	"
R 14	50000 Ω	0.5	"
R 15	50000 Ω	1	" Draht
R 16	500000 Ω	0.5	"
R 17	15000 Ω	0.5	"
R 18	1.5 M Ω	0.5	"
R 19	3000 Ω	0.5	"
R 20	5000 Ω	1	" Draht



Widerstände					
R	Widerstandwert	Belastung	Widerstandwert		
R 21	15000 Ω	0.5 Watt	R 33	20000 Ω	0.5 Watt
R 22	500 Ω	1 " Draht	R 34	70000 Ω	0.5 " "
R 23	30000 Ω	0.5 " "	R 35	1000 Ω	1 " Draht
R 24	500000 Ω	0.5 " "	R 36	5000 Ω	2 " "
R 25	1 M Ω	0.5 " "	R 37	90 Ω	Brumm.-Potentiom.
R 26	500000 Ω	0.5 " "	R 38	1 M Ω	Potentiom. Log.
R 27	2 M Ω	0.5 " "	R 39	4000 Ω	" geradl.
R 28	2000 Ω	1 " Draht	R 40	60000 Ω	Regel-widerstand
R 29	500000 Ω	0.5 " "	R 41	3000 Ω	0.5 Watt
R 30	600000 Ω	0.5 " "	R 42	3000 Ω	0.5 " "
R 31	100000 Ω	0.5 " "	R 43	1000 Ω	1 " Draht
R 32	100000 Ω	0.5 " "			

Ströme gem. m. Manometer u. Nebenwiderstand.  
 Spgen. " m. " u. 500V. Vorwiderstand.

# Schaltbild MENDE 355 W